



# Tip Cleaning System

Ref. CL9885

## Packing list

The following items should be included:

Tip Cleaning Stand ......1 unit Sponge .....1 unit Ref. S0354

Manual ...... 1 unit

Ref. CL9885







### **Features**

Improve thermal transfer by cleaning the tip after each solder joint.

#### Brass wool

Ref. CL6210

Very effective cleaning method. It leaves a small laver of solder on the tip to prevent oxidation between cleaning and rewetting

## Sponge

Ref. S0354

The least harmful cleaning method. Keep the sponge damp with destilled water when working to avoid tip wear

Non-slip base

#### Splashguard

It minimises splashing of solder particles when using the metal or brass wool

#### **Tip Wiper** Ref. CL0236

A temperature resistant receptacle allows the operator to remove excess solder by gently tapping or wiping

You don't need to hold the base while cleaning tips

#### Tapping:



Tap gently to remove the excess of solder

#### Wiping:



Use the slots to wipe off any remaining particles



## **Optional**

Inox wool Ref. CL6205

Brushes Ref. CL6220

**Tip-tinner** Ref. TT-A

Sand Ref. CL6211









## **Wool Replacement**





2



3



4



## Metallic Brush Replacement

1



2



3



4



## **Tip Wiper Replacement**

1



Wiper can be easily removed to clean it

## **Specifications**

Total weight: 0,9 kg (1.9 lb) Dimensions: 110 x 90 x 90 mm



#### Warranty

JBC's 2 year warranty covers this equipment against all manufacturing defects, including the replacement of defective parts and labour. Warranty does not cover product wear due to use or mis-use.

In order for the warranty to be valid, equipment must be returned, postage paid, to the dealer where it was purchased.



This product should not be thrown in the garbage.

In accordance with the European directive 2002/96/EC, electronic equipment at the end of their life must be collected and returned to an authorized recycling facility.